



Cat. No.	Watts/m	No. of LEDs/m	Colour	lm/m	lm/W
AA-ST12160CRGBW-30	16W	896	3000K	640lm	40
AA-ST12160CRGBW-40	16W	896	4000K	combined	

Accessories

AA-ST12CA	LEDline™ COB RGBW strip connector
AA-ST12CB	LEDline™ COB RGBW wired strip connector
AA-ST12CC	LEDline™ COB RGBW inter-connection strip connector
AA-ST12CD	LEDline™ COB RGBW single colour 90° strip connector
AA-ST10CD	LEDline™ COB single colour 90° strip connector

Cat. No.	Description	Metres per driver
----------	-------------	-------------------

LED Drivers

SV-LRS-35-24	35W non-dimmable 24V constant voltage driver	2m
SV-LRS-50-24	50W non-dimmable 24V constant voltage driver	3m
SV-LRS-75-24	75W non-dimmable 24V constant voltage driver	4.5m
SV-LRS-100-24	100W non-dimmable 24V constant voltage driver	5.5m
SV-LRS-150-24	150W non-dimmable 24V constant voltage driver	8.5m
SV-LRS-200-24	200W non-dimmable 24V constant voltage driver	10m

Max single run 5m

Product Features:

- COB RGBW flexible strip with 3M self adhesive backing
- Cut points every 63mm for maximum flexibility
- Beam angle of 120°
- 896 LEDs per metre
- For runs over 5m individual lengths should be connected in parallel
- Reel length of 30m

Line Drawing



Connectors

AA-ST12CA LEDline™ COB RGBW Strip Connector

AA-ST12CB LEDline™ COB RGBW wired strip connector


AA-ST12CC LEDline™ COB RGBW inter-connection strip connector

AA-ST12CD LEDline™ COB RGBW 90° strip connector

RGB Colour Changing



White Options



3000K

4000K

Warranty:

This product has a warranty period of 3 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserve the right to alter.